

TP 15 S4	Shi	Si-N	=2SC4151						
TP 15 T4	Shi	Si-P	=2SA1601						
TP 15 W45FX	Shi	Si-N	=2SC4582						
TP 107		Si-N	=BC 107	7c,7a,7e	TO-92	BC 546	7a		•BC 107
TP 108		Si-N	=BC 108	7c,7a,7e	TO-92	BC 546	7a		•BC 108
TP 109		Si-N	=BC 109	7c,7a,7e	TO-92	BC 550	7a		•BC 109
TP 251		Si-P	=BC 251	7c,7a,7e	TO-92	BC 556	7a		•BC 251
TP 252		Si-P	=BC 252	7c,7a,7e	TO-92	BC 556	7a		•BC 252
TP 253		Si-P	=BC 253	7c,7a,7e	TO-92	BC 560	7a		•BC 253
TP 3020	Nsc	CMOS-IC	Telecom, µ-Law CODEC	24-DIC					KT 8520, 2910
TP 3021	Nsc	CMOS-IC	Telecom, A-Law CODEC	22-DIC					KT 8521, 2911
TP 3040	Nsc	CMOS-IC	Telecom, PCM CODEC	16-DIC					ETC 5040, KT 3040, M 5912, µA 5912, 2912
TP 3051	Nsc	CMOS-IC	Telecom, A-Law/µ-Law PCM CODEC	20-DIC					-
TP 3052	Nsc	CMOS-IC	Telecom, A-Law/µ-Law PCM CODEC	18-DIC					-
TP 3053	Nsc	CMOS-IC	Telecom, A-Law/µ-Law PCM CODEC	20-DIC					-
TP 3054	Nsc	CMOS-IC	Telecom, µ-Law CODEC	16-DIC					ETC 5054, KT 3030, MB 6041, µA3054, 2916
TP 3056	Nsc	CMOS-IC	Telecom, A-Law/µ-Law PCM CODEC	20-DIC					-
TP 3057	Nsc	CMOS-IC	Telecom, A-Law CODEC	16-DIC					ETC 5057, KT 3032, MB 6042, µA3057, 2917
TP 3064	Nsc	CMOS-IC	•KT 3031	20-DIC					ETC 5064, MB 6045, KT 3031, KT 3064
TP 3067	Nsc	CMOS-IC	•KT 3033	20-DIC					ETC 5067, MB 6046, KT 3033
TP 3110	Nsc	CMOS-IC	Digital Line Interface Ctr. (DLIC)	40-DIC					-
TP 3120	Nsc	CMOS-IC	Digital Line Interface Ctr. (DLIC)	40-DIC					-
TP 3155	Nsc	CMOS-IC	•KT 8555	20-DIC					KT 8555
TP 3566		Si-N	•2N3566	7e	TO-92				-
TP 3638(A)		Si-P	•2N3638(A)	7a	TO-92				-
TP 3702...3711		Si-P/N	•2N3702...3711	7c	TO-92				-
TP 3702BR...3711BR		Si-P/N	•2N3702...3711	7a	TO-92				-
TP 4058...4062		Si-P	•2N4058...4062	7c	TO-92				-
TP 4123...4126		Si-N/P	•2N4123...4126	7a	TO-92				-
TP 4257...4258		Si-P	•2N4257...4258	7a	TO-92				-
TP 4274...4275		Si-N	•2N4274...4275	7a	TO-92				-
TP 5087(A)	Nsc	CMOS-IC	Telecom, Tastenwahl/DTMF Dialing	16-DIC					-
TP 5088	Nsc	CMOS-IC	Telecom, Tastenwahl/DTMF Dialing, Binary Input Data	14-DIC					-
TP 5092(A)	Nsc	CMOS-IC	Telecom, Tastenwahl/DTMF Dialing	16-DIC					-
TP 5094(A)	Nsc	CMOS-IC	Telecom, Tastenwahl/DTMF Dialing	16-DIC					-
TP 5116 A	Nsc	CMOS-IC	Telecom, µ-Law CODEC	16-DIC					KT 5116, M 5116, MK 5116, µA 5116
TP 5117 A	Nsc	CMOS-IC	Telecom, µ-Law CODEC	16-DIC					-
TP 5156 A	Nsc	CMOS-IC	Telecom, A-Law CODEC	16-DIC					-
TP 5393	Nsc	CMOS-IC	Telecom, Impulswahl/Pulse Dialing	18-DIP					-
TP 5394	Nsc	CMOS-IC	Telecom, Impulswahl/Pulse Dialing	16-DIP					-
TP 5395	Nsc	CMOS-IC	Telecom, Tastenwahl/DTMF Dialing	18-DIP					-
TP 5600	Nsc	CMOS-IC	Telecom, Impulswahl/Pulse Dialing, 10-No. Repertory	16-DIP					-
TP 5605	Nsc	CMOS-IC	Telecom, Impulswahl/Pulse Dialing, 10-No. Repertory	18-DIP					-
TP 5610	Nsc	CMOS-IC	Telecom, Impulswahl/Pulse Dialing, 10-No. Repertory	16-DIP					-
TP 5615	Nsc	CMOS-IC	Telecom, Impulswahl/Pulse Dialing, 10-No. Repertory	18-DIP					-
TP 5650	Nsc	CMOS-IC	Telecom, Tastenwahl/DTMF Dialing, 10-No. Repertory	16-DIP					-
TP 5660	Nsc	CMOS-IC	Telecom, Tastenwahl/DTMF Dialing, 10-No. Repertory	16-DIP					-
TP 9151	Nsc	CMOS-IC	Telecom, Tastenwahl/Pulse Dialer, Redial	18-DIC					-
TP 9152	Nsc	CMOS-IC	Telecom, Tastenwahl/Pulse Dialer, Redial	18-DIC					-
TP 9156	Nsc	CMOS-IC	Telecom, Tastenwahl/Pulse Dialer, Redial	18-DIC					-
TP 9158	Nsc	CMOS-IC	Telecom, Tastenwahl/Pulse Dialer, Redial	18-DIC					-
TP 50981(A)	Nsc	CMOS-IC	Telecom, Impulswahl/Pulse Dialer	16-DIP					KS 5804, LR 40981, MK 50981
TP 50982(A)	Nsc	CMOS-IC	Telecom, Impulswahl/Pulse Dialer	16-DIP					-
TP 50985(A)	Nsc	CMOS-IC	Telecom, Impulswahl/Pulse Dialer	16-DIP					-
TP 53125	Nsc	CMOS-IC	Telecom, Tastenwahl/DTMF Dialing	18-DIP					-
TP 53130	Nsc	CMOS-IC	Telecom, Tastenwahl/DTMF Dialing	18-DIP					-
TP 53143	Nsc	CMOS-IC	Telecom, Impulswahl/Pulse Dialing	18-DIP					-
TP 53144	Nsc	CMOS-IC	Telecom, Impulswahl/Pulse Dialing	16-DIP					-
TPS 141	Ssc	Si-P	LFS P, 70V, 10A, 75W, >0,8MHz	17j	TO-220	BD 810	17j		BD 710, BD 712, BD 808, BD 810
TPS 142	Ssc	Si-P	=TPS 141: 80V	17j	TO-220	BD 810	17j		BD 710, BD 712, BD 810
TPS 241(A...C)	Ssc	Si-N	•BD 241(A...C)	17j	TO-220				-
TPS 242(A...C)	Ssc	Si-P	•BD 242(A...C)	17j	TO-220				-
TPS 6512...6523	Spr	Si-N/P	•MPS 6512...6523	7a	SOT-30				-
TPS-A 13	Tix	Si-N-Darl	•MPS-A13	7c	TO-92				-
TPS-A 14	Tix	Si-N-Darl	•MPS-A14	7c	TO-92				-
TPU 2700	Itt	NMOS-IC	CTV, Vtx/Teletext Processor	40-DIP					-
TPU 2732	Itt	NMOS-IC	CTV, Vtx/Teletext Processor, PAL/NTSC	40-DIP					-
TPU 2733	Itt	NMOS-IC	CTV, Vtx/Teletext Processor, PAL/D2-MAC	40-DIP					-
TPU 2735	Itt	NMOS-IC	CTV, Vtx/Teletext Processor	40-DIP					-
TPU 2740	Itt	NMOS-IC	CTV, Vtx/Teletext Processor, PAL/NTSC/D2-MAC	40-DIP					-
TPU 2750	Itt	NMOS-IC	CTV, Vtx/Teletext Processor, f. NABTS	40-DIP					-
TPU 2760	Itt	NMOS-IC	CTV, Vtx/Teletext Processor, f. Japan	40-DIP					-
TQ		Si-P	=2SA1530-Q (SMD-Marking)	35	SOT-23				•2SA1530
TQ		Si-P	=2SA1603-Q (SMD-Marking)	35(2mm)	SOT-323				•2SA1603
TQ		Si-N	=2SD1119-Q (SMD-Marking)	39	SOT-89				•2SD1119
TQ		Si-N-Darl+Di	=2SD1699-TQ (SMD-Marking)	39	SOT-89				•2SD1699
TR		Si-P	=2SA1530-R (SMD-Marking)	35	SOT-23				•2SA1530
TR		Si-P	=2SA1603-R (SMD-Marking)	35(2mm)	SOT-323				•2SA1603
TR		Si-N	=2SC2406-R (SMD-Marking)	35	SOT-23				•2SC2406
TR		Si-N	=2SC3906K-R (SMD-Marking)	35	SOT-23				•2SC3906K
TR		Si-N	=2SC3929A-R (SMD-Marking)	35(2mm)	SOT-323				•2SC3929A
TR		Si-N	=2SC4102-R (SMD-Marking)	35(2mm)	SOT-323				•2SC4102
TR		Si-N	=2SD1119-R (SMD-Marking)	39	SOT-89				•2SD1119
TR		Si-N-Darl+Di	=2SD1699-TR (SMD-Marking)	39	SOT-89				•2SD1699
TR 22		Si-Di	=HVT 30S	31a		(BY 713)	31a		•HVT 30S
TR 30		Si-Di	=HVT 30E	31a		BY 713	31a		•HVT 30E
TS		Si-P	=2SA1530-S (SMD-Marking)	35	SOT-23				•2SA1530
TS		Si-P	=2SA1603-S (SMD-Marking)	35(2mm)	SOT-323				•2SA1603
TS		Si-N	=2SC2406-S (SMD-Marking)	35	SOT-23				•2SC2406
TS		Si-N	=2SC3906K-S (SMD-Marking)	35	SOT-23				•2SC3906K
TS		Si-N	=2SC3929A-S (SMD-Marking)	35(2mm)	SOT-323				•2SC3929A
TS		Si-N	=2SC4102-S (SMD-Marking)	35(2mm)	SOT-323				•2SC4102
TS		Z-Di	=SM 4T 200 (SMD-Marking)	71a(6x4mm)	SOD-6				•SM 4T....