

|               |              |   |         |          |
|---------------|--------------|---|---------|----------|
| AN 7140*      | LIN-IC       | NF-E, 24V, 4A, 5W(13V/4Ω)               | 9-SIL   |          |
| AN 7145 M     | LIN-IC       | 2x NF-E, 24V, 4A, 2x4,5W(16V/8Ω)        | 18-DILP |          |
| AN 7156 N*    | LIN-IC       | 2x NF-E, 24V, 4A, 2x5,5W(13V/4Ω)        | 12-SILP |          |
| AN 7158(N)*   | LIN-IC       | 2x NF-E, 24V, 4A, 2x7,5W(16V/4Ω)        | 12-SILP |          |
| AN 7160*      | LIN-IC       | NF-E, 24V, 4A, 17W(13V/4Ω)              | 12-SILP |          |
| AN 7161 N     | LIN-IC       | 2x NF-E, 26V, 4A, 23W(15V/4Ω), BTL      | 12-SILP |          |
| AN 7171 K     | LIN-IC       | 2x NF-E, 24V, 6A, 2x>9W(13V/4Ω), ON=+5V | 16-SQL  |          |
| AN 7178       | LIN-IC       | 2x NF-E, 18V, 4A, 2x5,7W(12V/3Ω)        | 12-SIP  |          |
| AN 7222(N)    | LIN-IC       | AM/FM-ZF, AFC, AGC, Demod.              | 18-DIP  |          |
| AN 7311*      | LIN-IC       | Auto-/Car-Radio, 2x NF-V, 18V           | 9-SIP   |          |
| BA 159        | Si-Di        | S, TV-Clamping, 1000V, 0,4A, <300ns     | 31a     |          |
| BA 222*       | LIN-IC       | CR Timer, Ucc=4,5...16V                 | 7-SIP   |          |
| BA 401*       | LIN-IC       | TV-Ton-ZF, FM-ZF                        | 5-SIP   |          |
| BA 402*       | LIN-IC       | TV-Ton-ZF, FM-ZF                        | 7-SIP   |          |
| BA 514*       | LIN-IC       | NF-V+E, 2W(9V/4Ω)                       | 8-SIL   |          |
| BA 527*       | LIN-IC       | NF-E, 0,8W(6V/4Ω)                       | 9-SIP   |          |
| BA 532        | LIN-IC       | NF-E, 5,8W(13V/4Ω)                      | 10-SIL  |          |
| BA 1310*      | LIN-IC       | FM-Multiplex Stereo-Decoder             | 14-DIP  |          |
| BA 1320*      | LIN-IC       | FM-Multiplex Stereo-Decoder, Ucc=12V    | 16-DIP  |          |
| BA 1330*      | LIN-IC       | =BA 1320: Ucc=3,6...6V                  | 16-DIP  |          |
| BA 5102 A     | LIN-IC       | VC, Audio-A/W-Verst., Logic             | 18-DIP  |          |
| BA 5410       | LIN-IC       | 2x NF-E, 20V, 2x5,2W(12V/3Ω)            | 10-SIL  |          |
| BA 6109       | LIN-IC       | VC, Motor-Tr(reversible), 18V, 0,8A     | 10-SIL  |          |
| BA 6209       | LIN-IC       | VC, Motor-Tr(reversible), 18V, 1,6A     | 10-SIL  |          |
| BA 6222       | LIN-IC       | VC, Motor-Tr(reversible), 18V, 2,2A     | 10-SIL  |          |
| BA 6247       | LIN-IC       | 2x Motor-Tr(reversible), 18V, 2W        | 10-SIL  |          |
| BAT 42        | Si-Di        | Schottky-Di, 30V, 0,2A, <5ns            | 31a     |          |
| BC 141        | Si-N         | NF-Tr/E, 100V, 1A, 0,75W, >50MHz        | 2a      | BC 161   |
| BC 161        | Si-P         | NF-Tr/E, 60V, 1A, 0,75W, >50MHz         | 2a      | BC 141   |
| BC 327        | Si-P         | NF-Tr, 50V, 0,8A, 0,625W, 100MHz        | 7a      | BC 337   |
| BC 337        | Si-N         | NF-Tr, 50V, 0,8A, 0,625W, 100MHz        | 7a      | BC 327   |
| BC 546        | Si-N         | Uni, 80V, 0,1A, 0,5W, 300MHz            | 7a      | BC 556   |
| BC 550        | Si-N         | =BC 547: ra                             | 7a      | BC 560   |
| BC 556        | Si-P         | Uni, 80V, 0,1A, 0,5W, 150MHz            | 7a      | BC 546   |
| BC 560        | Si-P         | =BC 557: ra                             | 7a      | BC 550   |
| BC 639        | Si-N         | NF-Tr/E, 100V, 1A, 0,8W, 130MHz         | 7c      | BC 640   |
| BC 640        | Si-P         | NF-Tr/E, 100V, 1A, 0,8W, 50MHz          | 7c      | BC 639   |
| BC 807(SMD)   | Si-P         | SMD, NF-Tr, 50V, 0,5A, 100MHz           | 35a     | BC 817   |
| BC 817(SMD)   | Si-N         | SMD, NF-Tr, 50V, 0,5A, 200MHz           | 35a     | BC 807   |
| BC 846(SMD)   | Si-N         | SMD, Uni, 80V, 0,1A, 300MHz             | 35a     | BC 856   |
| BC 848 C(SMD) | Si-N         | SMD, Uni, 30V, 0,1A, 300MHz             | 35a     | BC 858C  |
| BC 850 C(SMD) | Si-N         | SMD, Uni, ra, 50V, 0,1A, 300MHz         | 35a     | BC 860   |
| BC 856 B(SMD) | Si-P         | SMD, Uni, 80V, 0,1A, 150MHz             | 35a     | BC 846   |
| BC 858 C(SMD) | Si-P         | SMD, Uni, 30V, 0,1A, 150MHz             | 35a     | BC 848C  |
| BC 860 B(SMD) | Si-P         | SMD, Uni, ra, 50V, 0,1A, 150MHz         | 35a     | BC 850   |
| BC 879        | Si-N-Darl+Di | NF/S, 100V, 1A, 0,8W, 200MHz, B>2000    | 7c      | BC 880   |
| BC 880        | Si-P-Darl+Di | NF/S, 100V, 1A, 0,8W, 200MHz, B>2000    | 7c      | BC 879   |
| BD 139        | Si-N         | NF-L, 100V, 1,5A, 12,5W(Tc=45°),>50MHz  | 14h     | BD 140   |
| BD 140        | Si-P         | NF-L, 100V, 1,5A, 12,5W(Tc=45°),>50MHz  | 14h     | BD 139   |
| BD 189        | Si-N         | NF-L, 70V, 4A, 40W, 2MHz                | 14h     | BD 190   |
| BD 190        | Si-P         | NF-L, 70V, 4A, 40W, >2MHz               | 14h     | BD 189   |
| BD 237        | Si-N         | NF-L, 100V, 2A, 25W, >3MHz              | 14h     | BD 238   |
| BD 238        | Si-P         | NF-L, 100V, 2A, 25W, >3MHz              | 14h     | BD 237   |
| BD 243 C      | Si-N         | NF-L, 115V, 6A, 65W, >3MHz              | 17j     | BD 244 C |
| BD 244 C      | Si-P         | NF-L, 115V, 6A, 65W, >3MHz              | 17j     | BD 243 C |
| BD 245 C      | Si-N         | NF-L, 115V, 10A 80W >3MHz               | 18j     | BC 246 C |