

| Typ type | Art device | Bild figure | Ersatztyp replacement | Bild figure |
|-------------------|---------------|----------------|--------------------------|----------------|
| 2 N 2956 | Ge-P | 2a | - | |
| 2 N 2957 | Ge-P | 2a | - | |
| 2 N 3005 | 50Hz-Thy | 2a | (TAG 103 X) | 2a |
| 2 N 3006 | 50Hz-Thy | 2a | (BRX 49) | 7a |
| 2 N 3007 | 50Hz-Thy | 2a | (BRX 49) | 7a |
| 2 N 3008 | 50Hz-Thy | 2a | (BRX 49) | 7a |
| 2 N 3027 | F-Thy | 2a | (TAG 103 X) | 2a |
| 2 N 3028 | F-Thy | 2a | (BRX 49) | 7a |
| 2 N 3029 | F-Thy | 2a | (BRX 49) | 7a |
| 2 N 3053(S) | Si-N | 2a | BC 141 | 2a |
| 2 N 3053 A | Si-N | 2a | BC 141 | 2a |
| 2 N 3054(S) | Si-N | 22a | BD 243 C | 17j |
| 2 N 3054 A | Si-N | 22a | BD 243 C | 17j |
| 2 N 3055(E,H,S,U) | Si-N | 23a | 2N3055 | 23a |
| 2 N 3055 C,V | Si-N | 23a | 2N3055 | 23a |
| 2 N 3228 | 50Hz-Thy | 22a | 2N4101 | 22a |
| 2 N 3232 | Si-N | 23a | 2N3055 | 23a |
| 2 N 3257 | F-Thy | 2a | (TAG 103 X) | 2a |
| 2 N 3258 | F-Thy | 2a | (TAG 103 X) | 2a |
| 2 N 3259 | F-Thy | 2a | (BRX 49) | 7a |
| 2 N 3273 | 50Hz-Thy | 2a | (TIC 106 M) | 17e |
| 2 N 3274 | 50Hz-Thy | 2a | (TIC 106 M) | 17e |
| 2 N 3275 | 50Hz-Thy | 2a | (TIC 106 M) | 17e |
| 2 N 3276 | 50Hz-Thy | 2a | (TIC 106 M) | 17e |
| 2 N 3390 | Si-N | 7c | BC 546 | 7a |
| 2 N 3391(A) | Si-N | 7c | BC 546 | 7a |
| 2 N 3392 | Si-N | 7c | BC 546 | 7a |
| 2 N 3393 | Si-N | 7c | BC 546 | 7a |
| 2 N 3394 | Si-N | 7c | BC 546 | 7a |
| 2 N 3395 | Si-N | 7c | BC 546 | 7a |
| 2 N 3396 | Si-N | 7c | BC 546 | 7a |
| 2 N 3397 | Si-N | 7c | BC 546 | 7a |
| 2 N 3398 | Si-N | 7c | BC 546 | 7a |
| 2 N 3402 | Si-N | 7c | BC 639 | 7c |
| 2 N 3403 | Si-N | 7c | BC 639 | 7c |
| 2 N 3404 | Si-N | 7c | BC 639 | 7c |
| 2 N 3405 | Si-N | 7c | BC 639 | 7c |
| 2 N 3414 | Si-N | 7c | BC 639 | 7c |
| 2 N 3415 | Si-N | 7c | BC 639 | 7c |

| Typ type | Art device | Bild figure | Ersatztyp replacement | Bild figure |
|---------------|---------------|----------------|--------------------------|----------------|
| 2 N 3416 | Si-N | 7c | BC 639 | 7c |
| 2 N 3417 | Si-N | 7c | BC 639 | 7c |
| 2 N 3440(L,S) | Si-N | 2a | (MJE 340) | 14h |
| 2 N 3441 | Si-N | 22a | (BU 406) | 17j |
| 2 N 3441 X | Si-N | 22a | BD 243 C | 17j |
| 2 N 3441 Y | Si-N | 22a | BD 243 C | 17j |
| 2 N 3442 | Si-N | 23a | 2SD551 | 23a |
| 2 N 3502 | Si-P | 2a | BC 161 | 2a |
| 2 N 3503 | Si-P | 2a | BC 161 | 2a |
| 2 N 3525 | 50Hz-Thy | 22a | 2N4101 | 22a |
| 2 N 3553 | Si-N | 2a | - | |
| 2 N 3559 | 50Hz-Thy | 2a | TAG 103 X | 2a |
| 2 N 3560 | 50Hz-Thy | 2a | BRX 49 | 7a |
| 2 N 3561 | 50Hz-Thy | 2a | BRX 49 | 7a |
| 2 N 3562 | 50Hz-Thy | 2a | BRX 49 | 7a |
| 2 N 3566 | Si-N | 8a | BC 546 | 7a |
| 2 N 3567 | Si-N | 8a | BC 639 | 7c |
| 2 N 3568 | Si-N | 8a | BC 639 | 7c |
| 2 N 3569 | Si-N | 8a | BC 639 | 7c |
| 2 N 3611 | Ge-P | 23a | AL 102 | 23a |
| 2 N 3612 | Ge-P | 23a | AL 102 | 23a |
| 2 N 3613 | Ge-P | 23a | AL 102 | 23a |
| 2 N 3614 | Ge-P | 23a | AL 102 | 23a |
| 2 N 3615 | Ge-P | 23a | AL 102 | 23a |
| 2 N 3616 | Ge-P | 23a | AL 102 | 23a |
| 2 N 3617 | Ge-P | 23a | AL 102 | 23a |
| 2 N 3618 | Ge-P | 23a | AL 102 | 23a |
| 2 N 3638(A) | Si-P | 8a | BC 161 | 2a |
| 2 N 3641 | Si-N | 8a | BC 141 | 2a |
| 2 N 3642 | Si-N | 8a | BC 141 | 2a |
| 2 N 3643 | Si-N | 8a | BC 141 | 2a |
| 2 N 3662 | Si-N | 7c | BF 199 | 7d |
| 2 N 3663 | Si-N | 7c | BF 199 | 7d |
| 2 N 3702 | Si-P | 7c | BC 556 | 7a |
| 2 N 3703 | Si-P | 7c | BC 556 | 7a |
| 2 N 3704 | Si-N | 7c | BC 639 | 7c |
| 2 N 3705 | Si-N | 7c | BC 639 | 7c |
| 2 N 3706 | Si-N | 7c | BC 639 | 7c |
| 2 N 3707 | Si-N | 7c | BC 550 | 7a |