

TRANSISTOR NUMBER	PM OAL T	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
2N3571	NS	T072	L06	25V	15V	3V	50MA	200C	200MWF	1200M	DP85	20/200	5MA	ULA	SEU			0
2N3572	NS	T072	L06	25V	13V	3V	50MA	200C	200MWF	1000M	DP85	20/300	2MA	ULA	SEU			0
2N3576	PS	T018	L01	20V	15V	5V	200MA	200C	360MWF	400M	4P5	40/120	10MA	VLS	MOB	BSW25	2N3546	0
2N3577	NS	X51	X51	100V	80V		2A	175C	85WC	10M		12/60	1A	AMH	OBS			2
2N3579	PS	T046	L01	60V	60V		30MA	200C	400MWF	80M	6P	30/120	1MA	ALG	OBS	BC107	2N2510	2
2N3580	PS	T046	L01	60V	60V		30MA	200C	400MWF	80M	6P	60/240	1MA	ALG	OBS	BC107	2N2510	2
2N3581	PS	T046	L01	50V	40V		30MA	200C	400MWF	30M	6P	50/150	100UA	ALN	OBS	BC107C	2N2484	2
2N3582	PS	T046	L01	50V	40V		30MA	200C	400MWF	30M	6P	100MN	100UA	ALN	OBS	BC107C	2N2484	2
2N3583	NS	T066	L43	250V	175V	6V	1A	200C	35WC	10M		40/200	500MA	RME	SAS			1
2N3584	NS	T066	L43	375V	250V	6V	2A	200C	35WC	10M		25/100	1A	RHE	TIB			1
2N3585	NS	T066	L43	500V	300V	6V	2A	200C	35WC	10M		25/100	1A	RHE	TIB			1
2N3588	PG	T072	L06	25V			10MA	85C	100MWF	200M		20MN	1MA	ULA	OBS	AF239	2N3783	2
2N3589	NS	T05F	L44	200V			500MA	175C	2WC	15M		30/90	200MA	AME	OBS			2
2N3590	NS	T05F	L44	200V			500MA	175C	2WC	15M		75/150	200MA	AME	OBS			2
2N3591	NS	T012	L09	200V			500MA	175C	1WF	15M		30/90	200MA	AME	OBS			2
2N3592	NS	T012	L09	200V			500MA	175C	1WF	15M		75/150	200MA	AME	OBS			2
2N3593	NS	T0102	L59	200V			500MA	175C	1WF	15M		30/90	200MA	AME	OBS			2
2N3594	NS	T0102	L59	200V			500MA1	75C	1WF	15M		75/150	200MA	AME	OBS			2
2N3595	NS	T0102	L59	200V			500MA	175C	1.5WF	15M		30/90	200MA	AME	OBS			2
2N3596	NS	T0102	L59	200V			500MA	175C	1.5WF	15M		75/150	200MA	AME	OBS			2
2N3597	NS	T063	L60	60V	40V		20A	200C	100WC	30M	700P	40/120	10A	RHG	OBS	BLX28	2N5966	2
2N3598	NS	T063	L60	80V	60V		20A	200C	100WC	30M	700P	40/120	10A	RHG	OBS	BLX28	2N5966	2
2N3599	NS	T063	L60	100V	80V		20A	200C	100WC	30M	700P	40/120	10A	RHG	OBS	BLX28	2N5966	2
2N3600	NS	T072	L06	30V	15V	3V	50MA	200C	200MWF	850M	1P7	20/150	3MA	ULA	NAT	BFY90	2N5852	2
2N3601	PG	T05	L04	100V	40V		3A5	100C	500MWF	20M		60/180	1A	RHG	OBS		2N2667	2
2N3602	PG	X26	L59	100V	40V		3A5	100C	750MWF	20M		60/180	1A	RHG	OBS		2N2670	2
2N3603	PG	T05	L04	130V	55V		3A5	100C	500MWF	20M		60/180	1A	RHG	OBS		2N2667	2
2N3604	PG	X26	L59	130V	55V		3A5	100C	750MWF	20M		60/180	1A	RHG	OBS		2N2670	2
2N3605	NS	T098	L21	18V	14V	5V	200MA	150C	200MWF	300M	6P	30MN	10MA	VLS	SEU	BSX20	2N2369	2
2N3605A	NS	T098	L21	18V	14V	5V	200MA	120C	320MWF	300M	6P	30MN	10MA	VLS	OBS	BSX20	2N2369	2
2N3606	NS	T098	L21	18V	14V	5V	200MA	150C	200MWF	300M	6P	30MN	10MA	VLS	SEU	BSX20	2N2369	2
2N3606A	NS	T098	L21	18V	14V	5V	200MA	120C	320MWF	300M	6P	30MN	10MA	VLS	OBS	BSX20	2N2369	2
2N3607	NS	T098	L21	18V	14V	5V	200MA	150C	200MWF	300M	6P	30MN	10MA	VLS	SEU	BSX20	2N2369	2
2N3611	PG	T03	L05	40V	25V	20V	15A	110C	77WC	300K		35/70	3A	AHG	MOB	ASZ16	2N1536	0
2N3612	PG	T03	L05	60V	35V	30V	15A	110C	77WC	300K		35/70	3A	AHG	MOB	ASZ16	2N1536	0
2N3613	PG	T03	L05	40V	25V	20V	15A	110C	77WC	300K		60/120	3A	AHG	MOB	ASZ16	2N1536	0
2N3614	PG	T03	L05	60V	35V	30V	15A	110C	77WC	300K		60/120	3A	AHG	MOB	ASZ16	2N1536	0
2N3615	PG	T03	L05	80V	50V	40V	15A	110C	77WC	300K		30/60	3A	AHH	MOB	ASZ15	2N1533	0
2N3616	PG	T03	L05	100V	75V	50V	15A	110C	77WC	300K		30/60	3A	AHH	MOB	ASZ15	2N1533	0
2N3617	PG	T03	L05	80V	50V	40V	15A	110C	77WC	300K		45/90	3A	AHH	MOB	ASZ15	2N1533	0
2N3618	PG	T03	L05	100V	75V	50V	15A	110C	77WC	300K		45/90	3A	AHH	MOB	ASZ15	2N1533	0
2N3619	NS	T05	L04	75V	40V		2A5	175C	7.5WC	200M	50P	40MN	1A	RHG	OBS	BSV64	2N4877	2
2N3620	NS	T0102	L59	75V	40V		5A	175C	7.5WC	200M	50P	40MN	1A	RHG	OBS			2
2N3621	NS	T061	L46	75V	40V		10A	175C	30WC	200M	50P	40MN	1A	RHG	OBS	BDY63	2N5304	2
2N3622	NS	T061	L46	75V	40V		10A	175C	30WC	200M	50P	40MN	1A	RHG	OBS	BDY63	2N5304	2
2N3623	NS	T05	L04	75V	40V		2A5	175C	7.5WC	200M	50P	40MN	1A	RHG	OBS	BSV64	2N4877	2
2N3624	NS	T0102	L59	75V	40V		5A	175C	7.5WC	200M	50P	40MN	1A	RHG	OBS			2
2N3625	NS	T061	L46	75V	40V		10A	175C	30WC	200M	50P	40MN	1A	RHG	OBS	BDY63	2N5304	2
2N3626	NS	T061	L46	75V	40V		10A	175C	30WC	200M	50P	40MN	1A	RHG	OBS	BDY63	2N5304	2
2N3627	NS	T05	L04	100V	50V		2A5	175C	7.5WC	200M	50P	40MN	1A	RHG	OBS	BSV64	2N4877	2
2N3628	NS	T0102	L59	100V	50V		5A	175C	7.5WC	200M	50P	40MN	1A	RHG	OBS			2
2N3629	NS	T061	L46	100V	50V		10A	175C	30WC	200M	50P	40MN	1A	RHG	OBS	BDY63	2N5304	2
2N3630	NS	T061	L46	100V	50V		10A	175C	30WC	200M	50P	40MN	1A	RHG	OBS	BDY63	2N5304	2
2N3632	NS	T060	L61	65V	40V	4V	3A	200C	23WC	200M	20P	10MN	250MA	UMP	MOB			0
2N3633	NS	T018	L01	15V	6V		50MA	200G	300MWF	1300M	2P5	50/150	10MA	SLS	OBS		2N3960	2
2N3634	PS	T05	L04	140V	140V	5V	1A	200C	1WF	150M	10P	50/150	50MA	AME	MOB		2N3637	2
2N3634S	PS	T039	L04	140V	140V	5V	1A	200C	1WF	150M	10P	50/150	50MA	AME	MOB	BFT19	2N3634	2
2N3635	PS	T05	L04	140V	140V	5V	1A	200C	1WF	200M	10P	100MN	50MA	AME	MOB		2N3637	2
2N3635S	NS	T039	L04	140V	140V	5V	1A	200C	1WF	200M	10P	100MN	50MA	AME	MOB		2N3637	2
2N3636	PS	T05	L04	175V	175V	5V	1A	200C	1WF	150M	10P	50/150	50MA	AME	MOB		2N3637	2
2N3636S	PS	T039	L04	175V	175V	5V	1A	200C	1WF	150M	10P	50/150	50MA	AME	MOB	BFT19A	2N3636	2
2N3637	PS	T05	L04	175V	175V	5V	1A	200C	1WF	200M	10P	100MN	50MA	AME	MOB		2N3637	2
2N3637S	PS	T039	L04	175V	175V	5V	1A	200C	1WF	200M	10P	100MN	50MA	AME	MOB		2N3637	2
2N3638	PS	T0105	L04	25V	25V	4V	500MA		300MWF	100M	20P	30MN	50MA	AMG	SGI	BFS95	2N4036	0
2N3638A	PS	T0105	L04	25V	25V	4V	500MA	125C	300MWF	150M	10P	100MN	10MA	RMG	SGI	BFX29	2N2905A	0
2N3639	PS	T0105	L04	6V	6V	4V	80MA	125C	200MWF	500M	3P5	30/120	10MA	VLS	FCU	BSW25	2N3546	0
2N3640	PS	T0105	L04	12V	12V	4V	80MA	125C	200MWF	500M	3P5	30/120	10MA	VLS	FCU	BSW25	2N3546	0
2N3641	NS	T0105	L04	60V	30V	5V	500MA	125C	350MWF	250M	8P	40/120	150MA	AMG	SGI	BSW54	2N2219A	0
2N3642	NS	T0105	L04	60V	45V	5V	500MA	125C	350MWF	150M	8P	40/120	150MA	AMG	FCU	BFY50	2N2297	0
2N3643	NS	T0105	L04	60V	30V	5V	500MA	125C	350MWF	250M	8P	100MN	150MA	RMG	SGI	BSW54	2N2219A	0
2N3644	PS	T0105	L04	45V	45V	5V	500MA	125C	300MWF	200M	8P	115MN	50MA	RMG	SGI	BFX29	2N2905A	0
2N3645	PS	T0105	L04	60V	60V	5V	500MA	125C	300MWF	200M	8P	115MN	50MA	RMH	SGI	BFX29	2N2905A	0
2N3646	NS	T0106	L17	40V	15V	5V	200MA	125C	200MWF	350M	5P	30/120	30MA	RLS	SGI	BSX20	2N2369	0
2N3647	NS	T046	L01	40V	10V	6V	500MA	200C	400MWF	350M	4P	25/150	150MA	VLS	MOB	BSX20	2N2369	0
2N3648	NS	T046	L01	40V	15V	6V	500MA	200C	400MWF	450M	4P	30/120	150MA	VLS	MOB	BSX20	2N2369	0